

Application No: 10/735996 (Docket: CNTR.2152)  
37 CFR 1.111 Amendment dated 05/22/2007  
Reply to Office Action of 02/22/2007

RECEIVED  
CENTRAL FAX CENTER

MAY 22 2007

**AMENDMENTS TO THE CLAIMS**

Kindly amend claims 1, 11, and 21 as shown in the following listing of claims. The listing of claims will replace all prior versions, and listings, of claims in the application:

**Listing of Claims**

1. (Currently Amended) A microprocessor apparatus, for precluding a pipeline stall due to microcode ROM access delay, the microprocessor apparatus comprising:
  - a translator, configured to generate a plurality of micro instruction queue entries, each of said plurality of micro instruction queue entries corresponding to an instruction, and said each of said plurality of micro instruction queue entries comprising a plurality of micro instructions and a microcode entry point, wherein said translator generates said each of said plurality of micro instruction queue entries in order;
  - a micro instruction queue, coupled to said translator, configured to receive said each of said plurality of micro instruction queue entries in said order, and configured to provide said each of said plurality of micro instruction queue entries to register logic in said order;
  - a microcode ROM, configured to provide a second part of a micro instruction sequence corresponding to said microcode entry point; and

Application No. 10/735996 (Docket: CNTR.2152)  
37 CFR 1.111 Amendment dated 05/22/2007  
Reply to Office Action of 02/22/2007

early access logic, coupled to said micro instruction queue, configured to employ a selected microcode entry point~~said microcode entry point~~ from a selected one of said plurality of micro instruction queue entries to access said microcode ROM prior to when said selected microcode entry point is provided to said register logic, whereby said microcode ROM provides a first micro instruction from said second part to said register logic when said first micro instruction is required by said register logic, and wherein said early access logic employs said selected microcode entry point when said selected microcode entry point is positioned within said micro instruction queue a number of entries prior to transfer to said register logic that is equal to the number of excess clock cycles exhibited by the microcode ROM access delay over that already compensated for by configuration of said translator and said micro instruction queue~~within a bottom micro instruction queue entry, said bottom micro instruction queue entry comprising one of said each of said plurality of micro instruction queue entries, and wherein said bottom micro instruction queue entry will be provided to said register logic during a next clock cycle.~~

2. (Cancelled)
3. (Previously Presented) The microprocessor apparatus as recited in claim 1, wherein said plurality of micro instruction queue entries comprises four micro instruction queue entries.
4. (Original) The microprocessor apparatus as recited in claim 1, wherein said plurality of micro instructions comprises three micro instructions.
5. (Original) The microprocessor apparatus as recited in claim 4, wherein the microcode ROM access delay comprises four clock cycles.
6. (Cancelled)
7. (Cancelled)

Application No. 10/735996 (Docket: CNTR.2152)  
37 CFR 1.111 Amendment dated 05/22/2007  
Reply to Office Action of 02/22/2007

8. (Previously Presented) The microprocessor apparatus as recited in claim 1, wherein said translator is configured to provide a generated micro instruction queue entry to a top micro instruction queue entry, wherein said top micro instruction queue entry comprises one of said each of said plurality of micro instruction queue entries.
9. (Previously Presented) The microprocessor apparatus as recited in claim 1, wherein said translator is configured to provide a generated micro instruction queue entry to a mux, and, when said plurality of micro instruction queue entries is empty, said mux provides said generated micro instruction queue entry to said register logic during a next clock cycle.
10. (Original) The microprocessor apparatus as recited in claim 9, wherein said early access logic employs a bypass microcode entry point corresponding to said generated micro instruction queue entry.
11. (Currently Amended) An apparatus for absorbing pipeline stalls associated with microcode ROM access delay, the apparatus comprising:
  - a micro instruction queue, for receiving a plurality of queue entries in order from a translator, and for providing said plurality of queue entries to register logic in said order, each of said plurality of queue entries comprising:
    - first micro instructions, all of said first micro instructions corresponding to an instruction; and
    - a microcode entry point, coupled to said first micro instructions; and
  - a microcode ROM, configured to provide second micro instructions stored therein, and pointed to by said microcode entry point; and

Application No. 10/735996 (Docket: CNTR.2152)  
37 CFR 1.111 Amendment dated 05/22/2007  
Reply to Office Action of 02/22/2007

early access logic, coupled to said micro instruction queue, configured to employ a selected microcode entry point from a selected one of said plurality of micro instruction queue entries to access said microcode ROM prior to when said selected microcode entry point is provided to said register logic, whereby said microcode ROM provides a first one of second micro instructions to said register logic when said first one is required by said register logic, and wherein said early access logic employs said selected microcode entry point when said selected microcode entry point is positioned within said micro instruction queue a number of entries prior to transfer to said register logic that is equal to the number of excess clock cycles exhibited by the microcode ROM access delay over that already compensated for by configuration of said translator and said micro instruction queue.  
~~configured to employ said microcode entry point to access said microcode ROM prior to when said each of said plurality of queue entries is provided to said register logic, whereby a first one of said second micro instructions is provided to said register logic when said first one of said second micro instructions is required by said register logic, and wherein said early access logic employs said microcode entry point when said microcode entry point is within a bottom queue entry, said bottom queue entry comprising one of said each of said plurality of micro instruction queue entries, and wherein said bottom queue entry will be provided to said register logic during a next clock cycle.~~

12. (Cancelled)
13. (Previously Presented) The apparatus as recited in claim 11, wherein said plurality of queue entries comprises four queue entries.
14. (Original) The apparatus as recited in claim 11, wherein said first micro instructions comprise three micro instructions.
15. (Original) The apparatus as recited in claim 14, wherein the microcode ROM access delay comprises four clock cycles.

Application No. 10/735996 (Docket: CNTR.2152)  
37 CFR 1.111 Amendment dated 05/22/2007  
Reply to Office Action of 02/22/2007

16. (Cancelled)
17. (Previously Presented) The apparatus as recited in claim 11, wherein said translator is configured to generate said each of said plurality of micro instruction queue entries.
18. (Previously Presented) The apparatus as recited in claim 17, wherein said translator is configured to provide a generated queue entry to a top queue entry, wherein said top queue entry comprises one of said each of said plurality of micro instruction queue entries.
19. (Original) The apparatus as recited in claim 17, wherein said translator is configured to provide a generated queue entry to a mux, and, when said plurality of queue entries is empty, said mux provides said generated queue entry to said register logic during a next clock cycle.
20. (Original) The apparatus as recited in claim 19, wherein said early access logic employs a bypass microcode entry point corresponding to said generated micro instruction queue entry.
21. (Currently Amended) A method for precluding microprocessor pipeline stalls resulting from microcode ROM access delay, the method comprising:  
  
translating instructions and first providing first parts of micro instruction sequences within a corresponding each of a plurality of micro instruction queue entries in order to a micro instruction queue, and second providing the corresponding each of a plurality of micro instruction queue entries to register logic in the order;  
  
storing second parts of the micro instruction sequences within a microcode ROM;

Application No. 10/735996 (Docket: CNTR.2152)  
37 CFR 1.111 Amendment dated 05/22/2007  
Reply to Office Action of 02/22/2007

obtaining a microcode entry point from within one of the plurality of micro instruction queue entries in the micro instruction queue, the one of the plurality of micro instruction queue entries comprising one of the first parts of the micro instruction-sequences; sequences, wherein the one of the plurality of micro instruction queue entries is positioned within the micro instruction queue a number of entries prior to transfer to the register logic that is equal to the number of excess clock cycles exhibited by the microcode ROM access delay over that already compensated for by configuration of a translator and the micro instruction queue; and

employing the microcode entry point to access one of the second parts of the micro instruction sequences within the microcode ROM, wherein said employing is performed prior to when the one of the plurality of micro instruction queue entries is routed to the register logic in a following pipeline stage, and whereby said employing enables the second micro instructions to be provided to the following pipeline stage without incurring the microprocessor pipeline-stalls; and stalls.

~~selecting the microcode entry point from within a bottom micro instruction queue entry, the bottom micro instruction queue entry comprising the one of a plurality of micro instruction queue entries, wherein the bottom micro instruction queue entry will be provided to the following pipeline stage during a next clock cycle.~~

22. (Original) The method as recited in claim 21, further comprising:  
issuing the plurality of micro instruction queue entries in order to the following pipeline stage.
23. (Original) The method as recited in claim 22, wherein the plurality of micro instruction queue entries comprises four micro instruction queue entries.
24. (Original) The method as recited in claim 21, wherein the first micro instructions comprises three micro instructions.

Application No. 10/735996 (Docket: CNTR.2152)  
37 CFR 1.111 Amendment dated 05/22/2007  
Reply to Office Action of 02/22/2007

25. (Original) The method as recited in claim 24, wherein the microcode ROM access delay comprises four clock cycles.
26. (Cancelled)
27. (Original) The method as recited in claim 21, further comprising:  
generating a current microcode entry point as part of said translating.
28. (Original) The method as recited in claim 27, wherein said generating provides the current microcode entry point to a top micro instruction queue entry, and wherein the top micro instruction queue entry comprises another of the plurality of micro instruction queue entries.
29. (Original) The method as recited in claim 27, wherein said generating provides the current microcode entry point to a mux, and, when the plurality of micro instruction queue entries is empty, the mux provides the current microcode entry point to the following pipeline stage during a next clock cycle.